



FIX & FLASH

LIGHT-ACTIVATED REPAIR GLUE

SMART ADVANTAGES

- Ultra strong lasting bond
- Water resistant
- Temperature resistant from -20°C to + 80°C
- Good initial tack
- Adjustable until you shine the light
- Does not stick fingers instantly
- Solvent-free
- Non-hazardous
- Non-irritant
- Can be sanded and painted
- Translucent formula, no yellowing
- No drips

USES

Bostik Fix & Flash presents a new way of bonding and repairing small objects combining the advantages of multi-purpose and cyanoacrylate products: Adjustable and fast. Thanks to light curing technology, Fix & Flash delivers a 'bond on command' solution: Apply the glue, adjust the positioning of the materials if necessary, turn on the light – And it's done! Easy to use thanks to the dispenser and fine nozzle, it allows precise and clean application. More environmentally-friendly, Fix & Flash has no hazardous labelling. Batteries can also be replaced (2 x CR2016).

MATERIALS AND SURFACES

All materials, all surfaces.

Materials:

Porcelain, ceramics, glass, mirror, leather, wood, paper, carton, metal, fabrics*, hard plastics, tiles, concrete, brick, stone ...

**staining tests should be performed before use*

Surfaces:

Opaque and transparent, including bonding two opaque surfaces together



PRODUCT CHARACTERISTICS

➤ Aspect	Greenish gel / Transparent after drying
➤ Open time	< 1 min *
➤ Adjustment time	approx. 10 seconds *
➤ Drying time (with direct light application)	approx. 15 seconds **
➤ Light	LED (recreates natural UV light)

** These times can vary depending on the levels of natural UV light in the room
** This time can vary depending on the thickness of the glue layer*

Bostik Ltd.

Common Road, Stafford, ST16 3EH, United Kingdom
www.bostik.co.uk / www.fixnflash.uk

APPLICATION

MATERIALS AND SURFACES

All materials, all surfaces.

Materials:

Porcelain, ceramics, glass, mirror, leather, wood, paper, carton, metal, fabrics*, hard plastics, tiles, concrete, brick, stone ...

**staining tests should be performed before use*

Surfaces:

Opaque and transparent, including bonding two opaque surfaces together

PREPARATION

The substrates must be flat, dry and clean (dust and grease free), with no area unsuitable for adhesive use. Scrape to clean if required and remove dust. On polished or coated surfaces: Sand and remove any grease or dust, in order to facilitate bonding.

APPLICATION

STICK WITH FIX & FLASH (For best results ensure both surfaces are dry, clean and free from dust and grease)



1 Before first use:
Screw the nozzle onto the tube & remove the cap to use.



2 Apply a small amount of glue to create a continuous bead on the edges of the object.



3 You have time to reposition your objects. Wait at least 3 seconds for an initial tack.



4 Switch on the light, then shine it around the edge for 15 seconds.

ADAPT TIME FOR DIFFERENT MATERIALS IF NECESSARY. AFTER EACH USE, CLEAN THE NOZZLE & SCREW THE LID ON TIGHTLY.

CLEANING

Fresh glue: acetone

Dry glue: scraping

SHELF LIFE

12 months in its sealed original packaging, kept at +20°C. Once opened, your product will keep for several months, stored vertically away from light, in a cool and dry place.

PACKAGING

Code	SKU	PCB	GENCOD
30619199	Device + tube 5g	6	5010591012264

Bostik Ltd.

Common Road, Stafford, ST16 3EH, United Kingdom
www.bostik.co.uk / www.fixnflash.uk

SAFETY

Cyanoacrylate. Danger. Bonds skin and eyes in seconds. Keep out of the reach of children.

Read label before use.

IN CASE OF EYE CONTACT: Immediately flush with plenty of water. After initial flushing, remove any contact lenses and continue flushing for at least 15 minutes. Hold eyelids apart and consult a physician. Do not force eyes or any bonded skin apart. If medical advice is needed, have product container or label at hand. This product is not a toy.

CAUTION: The LED lamp emits a small quantity of ultra violet radiation. Direct exposure to strong light can damage the eyes. Do not look directly at or direct the light beam towards someone's face or animals. Caution. Do not mix used and new batteries. Do not change or mistake the batteries' position. Dispose the batteries in the proper bin reserved for recycling.

These recommendations for use are defined according to average use standards. They must be followed but do not exempt from preliminary tests, especially in case of first use and/or special conditions of use.

BOSTIK CONSUMER HOTLINE

Smart help +44 (0) 1785 272625



TECHNICAL DATA SHEET AV / March 2020

This disclaimer is issued by Bostik Limited ("the Company") and applies to the use of any products supplied by the Company ("the Products") displayed on this Technical Data Sheet ("TDS"). Please read this disclaimer carefully before using any of the Products. Using this TDS and/or the Product constitutes your acceptance of this disclaimer. Its contents shall prevail over any directions of use and any disclaimer and/or exclusion or limitation of liability of the Company which may appear on the packaging of the Products.

This disclaimer sets out the entire financial liability of the Company (including any liability for the acts or omissions of its employees, agents and sub-contractors) to any user of the Products ("Product User") in respect of any use made or resale by the Product User, of any of the Products in this TDS.

This disclaimer does not affect the Company's liability for death or personal injury arising from the Company's negligence in respect of the Products, nor its liability for fraud, or fraudulent misrepresentation, nor any other liability which cannot be excluded or limited under applicable law.

The Company's total liability however arising and whether caused by tort (including negligence and breach of statutory duty), breach of contract or otherwise, arising in connection with the use made or resale by the Product User of any of the Products in this TDS shall be limited to the price paid for the Product by the Product User.

The Company shall not be liable to the Product User for any pure economic loss, loss of profit, loss of business, depletion of goodwill or otherwise, in each case whether direct, indirect or consequential, or any claims (including in respect of personal injury insofar as not caused by the Company's negligence) for consequential compensation whatsoever (howsoever caused) which arise out of or in connection with the use made or resale by the Product User of any of the Products in this TDS.

The Company shall not be liable to the Product User in relation to any loss for any use which is inappropriate or use which is otherwise than in accordance with the relevant instructions for use of the Products in this TDS or on the Product. Product Users are advised to confirm the suitability of the Products by their own tests.

This TDS covers just one of a large range of products supplied by the Company.

Full information on these products and advice on application is freely available from our fully trained staff throughout the country. In addition, specialist technical advice is available from our Technical Services Department. This TDS supersedes all previous TDSs relating to the Products, and users of it must ensure that it is the current issue. Destroy all previous TDS, and if in any doubt, contact the Company, quoting the code number in the top right hand corner on the front of this document.

Sales	Tel: 0844 371 1192	Fax: 01785 241818	customer.service@bostik.com
Technical Advice	Tel: 0844 371 1197	Fax: 01785 272867	technical.service@bostik.com
Technical Data & COSHH (MSDS) Data Sheets	Tel: 01785 272625	Fax: 01785 212962	stafford.gatehouse@bostik.com

Bostik SA

Common Road, Stafford, ST16 3EH, United Kingdom

+44 (0) 1758 272625

www.bostik.co.uk / www.fixnflash.uk